



# PMi SERIES

*inverter generators*

**STAGE V**  
COMPLIANT





PETROL

# FREEDOM OF movement

Camping, tailgating, feel outdoorsy. Time to power up your leisure experience and enjoy your home away from home with all comforts: appliances and personal electronics at your fingertips with no battery-dependent worries.

Optimal solution to combine silent operation with less fuel consumption and tension stability. They guarantee maximum efficiency through the Economy Mode, that automatically adjusts the engine speed to the optimum level to provide excellent fuel economy and noise reduction. The PMi Inverter Series has a compact design and are equipped with a handle that allows you to carry the product easily.

The range is equipped with a 12 Volt battery charger + cables, useful for recharging your car battery.

- Stable power for safe operation of sensitive electronics
- Pramac OHV engine
- Low-oil level shutdown
- Economy mode for maximum fuel savings and noise reduction
- Ports for mobile electronics charging (USB and DC 12V)



PORTABILITY



SILENT LOW EMISSION



RECOIL



DURABILITY



USB



DIRECT CURRENT

## INVERTER TECHNOLOGY: HOW DOES IT WORK?

The inverter technology improves the power quality. Inverter generators stabilize the output tension and provide high quality energy, which controls and stabilize the electrical supply. It is ideal for powering smart electronics, even computer and mobile phone.

	PMi 1000	PMi 2000	PMi 3000
Single Phase Max Power	950 Watts	1900 Watts	3000 Watts
Single Phase Rated Power	850 Watts	1700 Watts	2800 Watts
Voltage	230 V	230 V	230 V
Running time at 50% load	3.2 Hours	3 Hours	6 Hours
Tank Capacity	2.1 Litres	3.5 Litres	10 Litres
Fuel consumption 50% (l/h)	0.66 l/h	1.20 l/h	1.60 l/h
Fuel	Petrol	Petrol	Petrol
Displacement	53 cc	113 cc	207 cc
Speed (rpm)	Variable	Variable	Variable
Starting System	Recoil	Recoil	Recoil
Guaranteed sound level (LWA)	89 LWA	89 LWA	96 LWA
Noise emission at 7 m	61 dB(A)	61 dB(A)	68 dB(A)
Dimensions LxWxH (mm)	480x250x395	535x305x460	555x400x450
Dry Weight	14 Kg	22 Kg	38 Kg
Socket type   Standard EU	1 x Schuko 230V 16A 1 x DC 12V 6A n°2 USB 5V 2A	2 x Schuko 230V 16A 1 x DC 12V 6A n°2 USB 5V 2A	2 x Schuko 230V 16A 1 x DC 12V 6A
Socket type   UK	1 x 230V 13A 3 Pin 1 x DC 12V 6A n°2 USB 5V 2A	2 x 230V 13A 3 Pin 1 x DC 12V 6A n°2 USB 5V 2A	2 x 230V 13A 3 Pin 1 x DC 12V 6A n°2 USB 5V 2A
Battery charger	✓	✓	✓
Economy Mode	✓	✓	✓
Oil guard	✓	✓	✓
Overload Protection	✓	✓	✓
Hour meter	✓	✓	✓
Volt meter	✓	✓	✓
Frequency meter	✓	✓	✓
Fuel level gauge	✓	✓	✓
Wheel kit	✓	✓	✓



YOUTUBE TUTORIAL

[www.pramac.com](http://www.pramac.com) | [www.pramacparts.com](http://www.pramacparts.com)